



**KNIGHT FIRE & SECURITY PRODUCTS LTD**  
Unit 84, Seawall Road Industrial Estate  
Tremorfa, Cardiff CF25 5TH  
Tel: 029 2048 8129  
Fax: 029 2048 9132  
<mailto:info@knightfireandsecurity.com>

Sealed against outside attack.

*Can be used with just the reed switch and no resistors – connect the yellow wire and the red wire.*



- ❶ To include 1 resistor, twist the red & white wires together to link, then connect the yellow wire.
- ❷ To include 2 resistors twist the red & white wires together to link then connect the green wire.

*Black and blue wires are the tamper loop*

- ❸ The magnet side needs to be fitted 25 – 30mm away from the reed side; this is the most efficient position.

Flush Magnetic Contact 4K76K8 CE



**Part Code: PDA904K76K8**

Security Grade 2 Environmental Class 3

Manufactured to EN50131

