




**KNIGHT FIRE & SECURITY PRODUCTS LTD**  
**Unit 84, Seawall Road Industrial Estate**  
**Tremorfa, Cardiff CF25 5TH**  
Tel: 029 2048 8129  
Fax: 029 2048 9132  
<mailto:info@knightfireandsecurity.com>

Flush Magnetic Contact 1KR x 2 CE

**Part Code: PDA901KR**

Security Grade 2 Environmental Class 3

Manufactured to PD6662



Sealed against outside attack.

Can be used with just the reed switch and no resistors – connect the yellow wire and the red wire.



To include 1 resistor, twist the red & white wires together to link, then connect the yellow wire.

To include 2 resistors twist the red & white wires together to link then connect the green wire.

Black and blue wires are the tamper loop

The operating gap is approx. 30mm.

