



**KNIGHT FIRE & SECURITY PRODUCTS LTD**  
**Unit 84, Seawall Road Industrial Estate**  
**Tremorfa, Cardiff CF25 5TH**  
Tel: 029 2048 8129  
Fax: 029 2048 9132  
<mailto:info@knightfireandsecurity.com>

Large 8 Terminal Surface Magnetic Contact 4K72K2 CE

**Part Code: PDM104K72K2**



Security Grade 2 Environmental Class 2


Manufactured to PD6662

With Lid Tamper

CE

Can be used with just the 4K7 resistor in parallel with the reed switch (resistor is wired across reed) if in a shared Zone. Connect to the 4<sup>th</sup> and 6<sup>th</sup> terminals achieve this. If you don't want to use the resistor merely cut it off

If it is an end of line contact, connect the 6<sup>th</sup> and 8<sup>th</sup> terminals, which will then also bring the serial 2K2 resistor in to play. The operating gap is approx. 50mm.



The Microswitch is for the lid tamper;  
connect to terminals 5 and 7  
Other terminals are spare.

